

# Blancco Mobile Diagnostics and Erasure

Created date	Updated date	Affects version	Fix version
23 Mar 2023	24 Mar 2023	Blancco Mobile Diagnostics & Erasure Blancco Eraser for Apple Devices	N/A

## Description

This page will provide step by step instructions on how to update communication settings for Blancco Mobile Diagnostics & Erasure. Same instructions apply for existing installations of Blancco Eraser for Apple Devices software.

Valid communication settings are required for report sending and may be required for license consumption as well.

## Step by step instructions

This chapter contains instructions how to update the existing configuration with Blancco Management Portal details to allow future license consumption and report sending to Management Portal.

1. Login to the Blancco Mobile Diagnostics & Erasure station.
2. Open "Settings" and navigate to "General"-tab.
3. Under "Blancco Management Portal Settings" section, update "Hostname/IP" with your Management Portal "Erasure Client Endpoint" and make sure proper port is defined.

Erasure client endpoint is region specific, to find out your endpoint follow the steps provided here: [How to confirm your Blancco Management Portal erasure client endpoint details?](#)

**Settings**

General | Input & Edit | Host | Shortcuts | Printer

Device | Diagnostics | Android | Windows | iOS | BlackBerry | Tizen

**User Interface Settings**

Language: English

Keyboard layout: us

Enable input method switching: ☐

Show requires attention view: ☐

Use large fonts: ☐

Screen saver timeout: Disabled

**Blancco Management Portal Settings**

Hostname/IP: classic.eu-west-1.blancco.cloud

Port: 443

Username: support@blancco.com

Password: .....

Verify BMP SSL certificate: ☐

Connection status: ●

Retry BMP operations: ☒

Timeout (s): 20 s

Number of attempts: 1

Ok Apply Cancel

4. Update the "Username" and "Password" fields accordingly with your Management Portal details.
5. After providing the updated details, connection will be automatically tested and "Connection status" indicator should turn green.
6. Click "Apply" to save the settings.